



# Directive Systems & Engineering

2702 Rodgers Terrace  
Haymarket, VA 20169-1628

[www.directivesystems.com](http://www.directivesystems.com)

703-754-3876

## 0.6 Dish Tripod Mount, Model DSEDHMOUNT

*All hardware is Stainless Steel unless otherwise noted.*

1/2" Galvanized Bolt	2
1/2" Galvanized Nut	2
1/2" Galvanized Split Lock Washer	2
1/2" Galvanized Flat Washer	2
1/2" Stainless Steel Flat Washer	1
1/2" Rubber Flat Washer	1
2" Galvanized U-Bolts	2
5/16"-18 Galvanized Hex Nuts	4
5/16" Galvanized Split Lock Washer	4
Large 1/2" Stainless Steel Fender Washer	1
Saddle	2
Steel Mounting Plate	1
Cast Aluminum Dish Mount	1

**BEFORE INSTALLING YOUR NEW ANTENNA, PLEASE BE SURE  
TO READ THE ENCLOSED WARNING PAMPHLET.**

### DSEDHMOUNT mounting instructions

The DSEDHMOUNT is a one-piece die cast mount for our 0.6m dish and can be used to mount the dish to a mast or a tripod. Since most installations are unique to a users' preference, we will cover getting the dish mounted to the mount and general suggestions on mounting to a mast/tripod.

First, locate one of the two galvanized 1/2" bolts, flat washer, lock washer and nut. Next locate the LARGE flat washer, 2 smaller flat washers and rubber washer. Place the bolt through the LARGE flat washer and then through the hole in the center of the dish (refer to Figure 1 for correct orientation). Next place the rubber washer on the **back** side of the dish and then a small flat washer. Slide the DHMount on next followed by another small flat washer, galvanized lock washer and nut and tighten. The rubber washer and flat washer that were placed between the back of the dish and the

DHMount fill the depression in the casting and prevent the center of the dish from distorting when tightened.



**Figure 1.**

The included steel mounting plate can be used for mast mounting or tripod mounting. Refer to Figure 2 for tripod orientation or Figure 3 for mast mounting, using the included 2" U-bolts, 5/16" hardware and aluminum saddles.



Figure 2.

### Directive Systems Warranty Policy

All Directive Systems antennas are built with the finest materials available. We take great pride in building a quality product that will give years of good service and performance. If there is a defect in materials or workmanship within 90 days of purchase, Directive Systems will repair or replace the defective part, free of charge, to the original purchaser. **DO NOT RETURN ANYTHING WITHOUT PRIOR AUTHORIZATION FROM DIRECTIVE SYSTEMS.** Please contact us either by phone or email describing the problem and we will work to resolve it.

If, after examining a new antenna you received, you are not satisfied, contact us immediately for return authorization and refund. **ANY ANTENNA THAT HAS BEEN MODIFIED WILL BE SUBJECT TO A RESTOCKING CHARGE. IF AN ANTENNA IS SO MODIFIED AS TO MAKE IT UNUSABLE, DIRECTIVE SYSTEMS RESERVES THE RIGHT TO REFUSE TO ACCEPT THE ANTENNA FOR RETURN.**





**Figure 3.**